

TITLE OF THE INVENTION  
IMAGE SENSING APPARATUS AND CONTROL METHOD THEREOF

FIELD OF THE INVENTION

5           The present invention relates to an image sensing apparatus, such as a digital camera, and a control method thereof.

BACKGROUND OF THE INVENTION

10           Conventionally, image sensing apparatus such as digital camera is known which records and reproduce a still picture or an moving picture with a recording medium such as a memory card having a solid state memory device as a recording medium. Some type of such an apparatus is  
15           provided with not only an optical finder (OVF) but also an electronic finder composed of a color liquid crystal panel or the like.

          Such image sensing apparatus with an electronic finder often keeps sensed images displayed on the electronic  
20           finder successively even when the sensed images are not actually recorded or stored on a storage medium. Under these circumstances, the operations for recording the sensed images, such as focusing and image saving, start only when the shutter is pressed.

25           With the above-mentioned conventional image sensing apparatus equipped with an electronic finder, however, keeping sensed images displayed on the electronic finder

during image sensing reduces the number of shots that can be taken because a large amount of power is consumed by the electronic finder, resulting in battery drain. On the other hand, lowering the operating frequency of the entire apparatus too much to reduce power consumption is not practical because it will increase the shutter time lag, the time required for the image sensing to be actually carried out after the shutter is pressed.

10 SUMMARY OF THE INVENTION

The present invention has been made to solve the problems of the prior art described above. An object of the present invention, for example, is to achieve power savings without increasing the shutter time lag.

15 According to the present invention, there is provided an image sensing apparatus, comprising:

an image sensor that senses an image of a subject to obtain a sensed image;

20 an operating frequency setting device that is capable of setting the operating frequency of said image sensing apparatus to at least any of a first operating frequency or a second operating frequency different from said first operating frequency; and

25 a display unit that is capable of electrically displaying the sensed image obtained by said image sensor, the display unit being capable of display operations at any

of said first or second operating frequency set by said operating frequency setting device.

According to the present invention, there is also provided a method for controlling an image sensing apparatus, comprising:

an image sensing step that senses an image of a subject to obtain a sensed image;

an operating frequency setting step that sets the operating frequency of said image sensing apparatus to at least any of a first operating frequency or a second operating frequency different from said first operating frequency at least; and

a display step that electrically displays the sensed image obtained in said image sensing step, in said display step said sensed image being displayed at said first or second operating frequency set in said operating frequency setting step.

According to the present invention, there is also provided a storage medium that stores a control program of an image sensing apparatus, said control program comprising:

a code for an image sensing step that senses an image of a subject to obtain a sensed image;

a code for an operating frequency setting step that sets the operating frequency of said image sensing apparatus to at least any of a first operating frequency

or a second operating frequency different from said first operating frequency; and

5 a code for a display step that electrically displays the sensed image obtained in said image sensing step, in said display step said sensed image being displayed at said first or second operating frequency set in said operating frequency setting step.

10 Other features and advantages of the present invention will be apparent from the following description taken in conjunction with the accompanying drawings, in which like reference characters designate the same or similar parts throughout the figures thereof.

#### BRIEF DESCRIPTION OF THE DRAWINGS

15 The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate embodiments of the invention and, together with the description, serve to explain the principles of the invention.

20 FIG. 1 is a block diagram showing the configuration of the image sensing apparatus according to a first embodiment of the present invention; and

FIGS. 2 to 5 are flowcharts of image sensing processing.

25

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of the present invention will now be described in detail in accordance with the accompanying drawings.

FIG. 1 is a block diagram showing the configuration of the image sensing apparatus according to a first embodiment of the present invention. This device is configured, for example, as a digital camera.

In the figure, reference numeral 100 denotes an image processing apparatus (image sensing apparatus), 10 denotes a taking lens consisting of a zoom lens and focusing lens, 12 denotes a shutter provided with an aperture adjustment function, and 14 denotes an image sensing device, which converts an optical image into an electrical signal. Reference numeral 16 denotes an A/D converter, which converts the analog signal output of the image sensing device 14 into a digital signal. Reference numeral 18 denotes a timing generator circuit, which supplies clock signals and control signals to the image sensing device 14 and A/D converter 16 and is controlled by a memory control circuit 22 and system control circuit 50.

Reference numeral 20 denotes an image processing circuit, which performs designated pixel interpolation or color conversion on the data from the A/D converter 16 or data from the memory control circuit 22. The image processing circuit 20 carries out designated computations using sensed image data. Based on the computed results, the system control circuit 50 instructs the exposure

controller 40 and focusing controller 42 to perform TTL (through-the-lens) mode AF (autofocusing), AE (automatic exposure), and EF (preflashing) processes. Moreover, the image processing circuit 20 carries out designated  
5 computations using sensed image data, and based on the computed results, it performs a TTL mode AWB (automatic white balance) adjustment.

Reference numeral 22 denotes the memory control circuit, which controls the A/D converter 16, the timing  
10 generator circuit 18, the image processing circuit 20, an image display memory 24, a D/A converter 26, a memory 30, and a compression/decompression circuit 32.

The data from the A/D converter 16 is written into the image display memory 24 or memory 30 via the image  
15 processing circuit 20 and memory control circuit 22 or directly via the memory control circuit 22.

Reference numeral 24 denotes the image display memory, 26 denotes the D/A converter, and 28 denotes an image display section constituted by a TFT-LCD (thin film  
20 transistor liquid crystal display) and the like. The image data written into the image display memory 24 is displayed by the image display section 28 via the D/A converter 26. The image display section 28 can achieve the function of an electronic finder if it displays sensed image data  
25 successively. Also, it can turn on and off the display at any time in accordance with instructions from the system control circuit 50. Turning off the display helps reduce

the power consumption of the image processing apparatus 100 greatly.

Reference numeral 30 denotes a memory for storing still pictures or moving pictures as well as voice data. It has  
5 enough storage capacity to store a designated number of still pictures or designated minutes of moving pictures. This allows a large volume of image data to be written into the memory 30 at high speed even during sequential  
photography or panoramic photography which involves taking  
10 a series of still pictures successively. The memory 30 can also be used as a working area by the system control circuit 50.

Reference numeral 32 denotes a  
compression/decompression circuit, which compresses and  
15 decompresses image data through adaptive discrete cosine transform (ADCT) or the like. The circuit compresses or decompresses image data read from the memory 30 and writes the resulting data back into the memory 30.

Reference numeral 40 denotes an exposure controller,  
20 which controls the shutter 12 and can have a flash control function if linked with a flash 404. Reference numeral 42 denotes a focusing controller, which controls the focusing of the taking lens 10. The exposure controller 40 and focusing controller 42 are controlled by means of a TTL  
25 system. The system control circuit 50 controls the exposure controller 40 and focusing controller 42, based

on the results of the computations performed by the image processing circuit 20 on sensed image data.

Reference numeral 44 denotes a zoom controller, which controls the zooming of the taking lens 10. Reference numeral 46 denotes a barrier controller, which controls a protector 102 that serves as a barrier. Reference numeral 48 denotes a connector, also known as an accessory shoe, which incorporates an electric contact and mechanical clamp for flash apparatus 400.

10 Reference numeral 50 denotes a system control circuit, which controls the entire image processing apparatus 100. Reference numeral 52 denotes a memory, which stores the constants, variables, programs, etc. for the operation of the system control circuit 50.

15 Reference numeral 54 denotes a display section, which is constituted by a liquid crystal display, speaker, etc. This section displays operating state, messages, and the like using characters, images, voice, etc. according to the program executed by the system control circuit 50. The display section 54 is installed at one or more readily visible locations near input devices of the image processing apparatus 100 and constituted by, for example, a combination of an LCD (liquid crystal display), LEDs (light emitting diodes), sound-producing elements and the like.

25 Reference numeral 56 denotes an electrically erasable programmable non-volatile memory such as an EEPROM



(electrically erasable and programmable read only memory).  
Reference numerals 60, 61, 62, 64, 66, and 70 denote input  
devices, via which various instructions for the system  
control circuit 50 are entered and which are constituted  
5 by one or more switches, dials, touch panels, pointing  
devices employing line-of-sight detection, speech  
recognition devices, etc. or their combinations.

Now the input devices 60, 61, 62, 64, 66, and 70 will  
be described concretely.

10 Reference numeral 60 denotes a power switch that turns  
on and off the image processing apparatus 100. Reference  
numeral 61 denotes a mode dial switch, which allows  
selection among various modes such as automatic shooting  
mode, manual shooting mode, panoramic photography mode,  
15 playback mode.

Reference numeral 62 denotes a shutter switch (SW1),  
which turns on halfway through the release operation of a  
shutter button (not shown) and gives the command to start  
AF (autofocusing), AE (automatic exposure), AWB (automatic  
20 white balance), EF (preflashing), and other processes.

Reference numeral 64 denotes a shutter switch (SW2),  
which turns on when the release operation of the shutter  
button (not shown) is completed and triggers a sequence of  
processes: an exposure process of writing the signals read  
25 out of the image sensing device 12 into the memory 30 as  
image data through the A/D converter 16 and memory control  
circuit 22; developing process using the computations

carried out in the image processing circuit 20 and memory control circuit 22; and recording process of reading image data out of the memory 30, compressing it in the compression/decompression circuit 32, and writing it in a recording medium 200 or recording medium 210.

Reference numeral 66 denotes an image display ON/OFF switch, which allows the image display section 28 to be set to ON or OFF. This function makes it possible to shut off the current to the image display section constituted by an TFT-LCD, etc. during photography by the use of an optical finder 104, and thereby save power. The ON/OFF setting of the image display section 28 is stored as an image display flag (ON/OFF) in a memory 52. The user can set the image display flag at will using the input device 70. The setting may also be stored in an internal memory of the system control circuit 50.

A zoom switch (not shown) instructs zooming of the taking lens 10.

Reference numeral 70 denotes the input device, which consists of various buttons, a touch panel, etc., including a menu button, set button, macro button, multi-screen playback/page-break button, flash setting button, single-shot/multi-shot self-timer switchover button, menu forward (+) button, menu backward (-) button, image forward (+) button, image backward (-) button, menu up button, menu down button, picture quality selection button, exposure compensation button, date/time setting button, etc.

Reference numeral 80 denotes a power supply controller, which is constituted by a battery detector circuit, DC/DC converter, and switching circuit for switching the block to turn on. This controller detects the presence or absence of a battery, type of battery, and remaining battery capacity, and supplies required voltages for required periods of time to various parts of the system, including the recording media 200 and 210, by controlling the DC/DC converter, based on the results of the detection and instructions from the system control circuit 50.

Reference numerals 82 and 84 denote connectors while reference numeral 86 denotes a power supply, which is constituted by a primary battery such as an alkaline or lithium cell, secondary battery such as an NiCd, NiMH, or Li cell, AC adaptor, etc.

Reference numerals 90 and 94 denote interfaces (I/F) to the recording media 200 and 210 such as memory cards or hard disks while reference numerals 92 and 96 denote connectors for connecting to the recording media 200 and 210 such as memory cards or hard disks.

Reference numeral 98 denotes a media detector, which detects whether the recording medium 200 or 210 has been inserted in the connectors 92 and/or 96.

This embodiment has two sets of an interface and connector for connecting storage media. Of course, the present invention may be configured to have either one set or multiple sets of an interface and connector for

connecting recording media. Also, it may be configured to have a combination of interfaces and connectors of different standards.

Cards that comply with PCMCIA, CF (compact flash), or other similar standards may be used as the interfaces and connectors. When cards that comply with PCMCIA, CF (compact flash), or other similar standards are used for the interfaces 90 and 94 and connectors 92 and 96, if communications cards such as a LAN card, modem card, USB card, IEEE1394 card, P1284 card, SCSI card, and/or telecommunication card for PHS are connected, image data and accompanying management information can be exchanged with other computers or peripherals such as printers.

Reference numeral 102 denotes the barrier or protector 102, which covers an image sensing section including the taking lens 10 of the image processing apparatus 100 to protect the image sensing section from contamination and damage. Reference numeral 104 denotes the optical finder, which allows the user to take photographs only by using the optical finder 104 without using the electronic finder function of the image display section 28. Besides, the optical finder 104 incorporates some of the functions of the display section 54: for example, an in-focus indicator function, blur warning function, flash charge indicator function, shutter speed indicator function, f-number indicator function, exposure compensation indicator function.

Reference numeral 110 denotes a communications section, which has various communications functions such as RS232C, USB, IEEE1394, P1284, SCSI, modem, LAN, and wireless communications functions. Reference numeral 112  
5 denotes either a connector used to connect the image processing apparatus 100 to other equipment through the communications section 110 or an antenna used for wireless communications.

Reference numeral 200 denotes the storage medium such  
10 as a memory card or hard disk. The storage medium 200 has a recording section 202 constituted by a semiconductor memory, magnetic disk, or the like; an interface (I/F) 204 to the image processing apparatus 100; and a connector 206 for connecting to the image processing apparatus 100.

Reference numeral 210 denotes the storage medium such  
15 as a memory card or hard disk. The storage medium 210 has a recording section 212 constituted by a semiconductor memory, magnetic disk, or the like; an interface (I/F) 214 to the image processing apparatus 100; and a connector 216  
20 for connecting to the image processing apparatus 100.

Reference numeral 400 denotes the flash apparatus and 402 denotes a connector for connecting to the accessory shoe of the image processing apparatus 100. Reference numeral 404 denotes a flash, which is provided with an AF fill-  
25 flash function and flash control function.

With the above configuration, if the mode dial switch 61 is set at image sensing mode, the image sensing can be

carried out with the shutter switch (SW1) 62 and shutter switch (SW2) 64. The system control circuit 50 is normally ready for photography. If a press of the shutter switch (SW1) 62 is detected, the exposure controller 40 controls exposure and the focusing controller 42 controls focusing. When these control operations are completed, the system gets ready to start exposure. When a press of the shutter switch (SW2) 64 is detected, the exposure is started. The sensed image acquired by photography is stored in the memory 30 via the image sensing device 14, A/D converter 16, image processing circuit 20, and memory control circuit 22. The recorded image stored in the memory 30 are compressed by the compression/decompression circuit 32 as required, and stored again in the memory 30. The system control circuit 50 finishes photography in this state.

FIGS. 2 to 5 are drawings showing flowcharts of the image sensing processing according to this embodiment.

First, during initialization, i.e., upon power-up after a battery replacement or the like, the system control circuit 50 initializes flags and control variables (Step S101). Next, the system control circuit 50 checks the state of the power switch 60 to see if it is set at ON (Step S102). If the power switch 60 is set at OFF, the system control circuit 50 performs finishing processes (Step S105). Specifically, it finishes the display in the display sections, closes the barrier of the protector 102 to protect the image sensing section, stores necessary set values and

mode settings as well as the settings of necessary parameters including flags and control variables in the non-volatile memory 56, shuts off unnecessary power to individual sections of the image processing apparatus 100 including the image display section 28 by means of the power supply controller 80, and performs other designated finishing processes. Then the flow returns to the Step S102.

On the other hand, if it is found in the Step S102 that the power switch 60 is set at ON, the system control circuit 50 checks the setting position (either photo mode or playback mode) of the mode dial switch 61 to see if it is set at photo mode (Step S103). If it is found that the mode dial switch 61 is set at playback mode, the system control circuit 50 runs the playback process (Step S104) and returns to the Step S102.

If the mode dial switch 61 is set at photo mode, the system control circuit 50 checks the remaining capacity and operating state of the power supply 86 by using the power supply controller 80 to see if the operation of the image processing apparatus 100 will not be hampered (Step S106). If it is judged that the operation of the image processing apparatus 100 will be hampered, the system control circuit 50 goes to Step S109. If it is judged that the operation of the image processing apparatus 100 will not be hampered, the system control circuit 50 checks the operating state of the recording medium 200 or 210 to see if the operation

of the image processing apparatus 100, especially the recording and playback operations of image data with respect to the recording medium 200 or 210, will not be hampered (Step S107). If it is judged that the operation  
5 of the image processing apparatus 100 will be hampered, the system control circuit 50 goes to Step S109. If it is judged that the operation of the image processing apparatus 100 will not be hampered, the system control circuit 50 initializes the taking lens 10 and checks if it operates  
10 normally (Step S108). If it is judged that the taking lens 10 does not operate normally, the system control circuit 50 goes to Step S109.

In Step S109, the system control circuit 50 displays warnings in the display section 54, etc. using images or  
15 voice. Then the flow returns to the Step S102.

On the other hand, if it is judged in the Step S108 that the taking lens 10 operates normally, the system control circuit 50 checks if the image display flag is ON (Step S110 in FIG. 3). If it is found that the image display  
20 flag is ON, the system control circuit 50 switches the operating frequency W of the present apparatus as a whole to a first operating frequency W1 (Step S118).

The operating frequency W of the present apparatus is set either at the first operating frequency W1 or at a second  
25 operating frequency W2 higher than it. At the start of processing (initialization) in FIG. 2, it is set at the second operating frequency W2. Therefore, in the Step S118,



the operating frequency W is switched from the second operating frequency W2 to the first operating frequency W1, the lower frequency. This reduces power consumption. The switching of the operating frequency W is controlled by the  
5 system control circuit 50.

Next, the system control circuit 50 checks the state of image display in the image display section 28 to see if the image display in the image display section 28 is ON (Step S119). If it is found that the image display in the image display section 28 is not ON, the system control circuit  
10 50 turns on the image display in the image display section 28 (Step S120), puts it in through-display mode so that sensed image data will be displayed successively (Step S121), and goes to Step S122. On the other hand, if it is  
15 found that the image display in the image display section 28 is ON, the system control circuit 50 goes to the Step S122 immediately. In the through-display mode described above, the data written successively into the image display memory 24 via the image sensing device 14, A/D converter  
20 16, image processing circuit 20, and memory control circuit 22 is displayed successively in the image display section 28 via the memory control circuit 22 and the D/A converter 26 to implement the function of an electronic finder.

In the following Step S122, the system control circuit  
25 50 checks to see if a setting state indicator flag is ON. If it is ON, the system control circuit 50 displays the setting state in the image display section 28 (Step S123)

and goes to Step S131 in FIG. 4. On the other hand, if the setting state indicator flag is not ON, the system control circuit 50 goes to the Step S131 immediately.

If it is found in the Step S110 that the image display flag is not ON (i.e., the flag is OFF), the system control circuit 50 checks to see if the setting state indicator flag is ON (Step S111). If the setting state indicator flag is not ON, the system control circuit 50 goes to the Step S131 immediately. If the setting state indicator flag is ON, the system control circuit 50 turns on the image display in the image display section 28 (Step S112), displays the setting state in the image display section 28 (Step S113), and checks to see if a preset setting state display time has expired (Step S114). The system control circuit 50 continues the checking until the setting state display time expires. When the setting state display time expires, the system control circuit 50 turns off the setting state indicator flag (Step S115), clears the setting state display in the image display section 28 (Step S116), turns off the image display in the image display section 28 (Step S117), and goes to the Step S131.

In the following Step S131 in FIG. 4, the system control circuit 50 checks to see if the shutter switch (SW1) 62 is ON. If it is found that SW1 is not ON, the system control circuit 50 checks to see if the image display flag is ON (Step S152). If it is found that the image display flag is ON, the system control circuit 50 performs metering (Step

S153) and AWB adjustment (Step S154) and returns to the Step S102 in FIG. 2. On the other hand, if it is found that the image display flag is not ON, the system control circuit 50 returns to the Step S102 immediately.

5        If it is found in the Step S131 that the shutter switch (SW1) 62 is ON, the system control circuit 50 checks to see if the image display flag is ON (Step S132). If it is found that the image display flag is ON, the system control circuit 50 goes to Step S134. If it is found that the image display flag is not ON, the system control circuit 50 switches the operating frequency W (Step S133) before going to the Step S134.

10        This process of switching the operating frequency W changes the operating frequency W of the present apparatus as a whole from the first operating frequency W1 to the second operating frequency W2. Thus, the operating frequency W returns to its normal rate. This ensures that subsequent recording operations of sensed images, including metering, focusing control, and recording/saving operations, will be carried out at high speed.

15        Next, in Step S134, metering is performed. During metering, flash settings are made as required. In the following Step S135, focusing control is performed to focus the taking lens on the subject.

25        In the following Step S138, the system control circuit 50 checks to see if the shutter switch (SW2) 64 is ON. If it is found that SW2 is not ON, the system control circuit

50 checks to see if the shutter switch (SW1) 62 is ON (Step S139). If it is found that SW1 is not ON (has been turned off), the system control circuit 50 returns to the Step S102. If it is found that SW1 is ON (remains ON), the system control circuit 50 returns to the Step S138. If it is found in the Step S138 that the shutter switch (SW2) 64 is ON, the system control circuit 50 checks to see if the image display flag is ON (Step S140 in FIG. 5).

If it is found that the image display flag is ON, the system control circuit 50 sets the display mode in the image display section 28 to fixed color display mode (Step S141) and goes to Step S142. If it is found that the image display flag is not ON, the system control circuit 50 goes to the Step S142 immediately. In the fixed color display mode, instead of the sensed image data written into the image display memory 24 via the image sensing device 14, A/D converter 16, image processing circuit 20, and memory control circuit 22; fixed-color image data is received by the image display section 28 via the memory control circuit 22 and D/A converter 26 to display a fixed-color picture.

In the following Step S142, photographic processing is carried out. Specifically, the system control circuit 50 carries out exposure processing which involves writing photographic image data into the memory 30 via the image sensing device 14, A/D converter 16, image processing circuit 20, and memory control circuit 22 or directly from the A/D converter 16 via the memory control circuit 22 and

performs developing which involves reading the image data from the memory 30 using the memory control circuit 22 and, as required, image processing circuit 20 to perform various processing.

5           Next, the system control circuit 50 checks to see if the image display flag is ON (Step S143). If it is found that the image display flag is not ON, the system control circuit 50 turns on the image display in the image display section 28 (Step S144) and goes to Step S145. If it is found  
10           that the image display flag is ON, the system control circuit 50 goes to Step S145 immediately.

          In Step S145, the system control circuit 50 displays a quick review. If the Step S144 is skipped, the image display section 28 continues to display the sensed image, serving the function of an electronic finder, and the quick  
15           review is also displayed immediately after shooting. On the other hand, if the Step S144 is performed, the sensed image is not displayed for a quick review until just after shooting.

20           Next, the recording process of the sensed image data is carried out (Step S146). Specifically, this process involves reading the sensed image data from the memory 30, performing various image processing on it using the memory control circuit 22 and, as required, image processing  
25           circuit 20, compressing it by the compression/decompression circuit 32 according to the mode

setting, and then writing it into the recording medium 200 or 210.

Next, the system control circuit 50 checks to see if the image display flag is ON (Step S147). If it is found  
5 that the image display flag is ON, the system control circuit 50 sets the display mode to through-display (Step S148) and goes to Step S149. In the through-display mode, the sensed image data for the next shot is displayed successively after a quick review of the sensed image.

10 On the other hand, if it is found in the Step S147 that the image display flag is not ON, the system control circuit 50 turns off the image display in the image display section 28 (Step S150), turns on the setting state indicator flag (Step S151), and goes to the Step S149.

15 In the following Step S149, the system control circuit 50 checks to see if the shutter switch (SW1) 62 is ON. If it is found that SW1 is ON, the system control circuit 50 returns to the Step S138 to get ready for shooting. If it is found that SW1 is not ON (has been turned off), this means  
20 that the sequence of photographic operations is finished and the system control circuit 50 returns to the Step S102.

According to this processing, if the image display flag is ON, the operating frequency W of the apparatus is set at the lower, first operating frequency W1 until the shutter  
25 switch (SW1) 62 is pressed, and when the SW1 is pressed, the operating frequency W of the apparatus is switched to the second operating frequency W2, the normal frequency,

before metering, focusing control, etc. On the other hand, if the image display flag is OFF, the operating frequency W of the apparatus is constantly set at the normal, second operating frequency W2.

5           According to this embodiment, when a sensed image is displayed for image sensing, the apparatus operates at the lower, first operating frequency W1 until the shutter switch (SW1) 62 is pressed triggering the operations (metering, focusing control, saving, etc.) for recording  
10 the sensed image. This effectively reduces power consumption, which tends to be increased by the image display in the image display section 28. Besides, during the recording of sensed images, the apparatus operates at the normal, second operating frequency W2 to increase the  
15 processing speed and reduce the shutter time lag. Thus, power savings can be achieved without increasing the shutter time lag.

When the image sensing is carried out without sensed image display, since the image display section 28 consumes  
20 less power from the beginning, the decrease in the operating frequency is less effective in power savings. Therefore, the apparatus is always made to operate at the normal, second operating frequency W2 to give priority to the processing speed and avoid increasing the shutter time lag  
25 more reliably.

Although in this embodiment, the process of lowering the operating frequency W to the first operating frequency

W1 is applied to the entire apparatus, it is also possible to apply this process only to the operations (image sensing operation by the image sensing device 14, display operation by the image display section 28, etc.) directly relevant to the image display in the image display section 28.

Although in this embodiment, the timing of switching the operating frequency W from the first operating frequency W1 back to the second operating frequency W2 is provided after SW1 is pressed but before the metering (Step S134) to reduce the shutter time lag effectively, this timing is not limited to this time interval. It may be provided before the metering (Step S134), or after the shutter switch (SW2) 64 is pressed (Step S138) but before the photographic processing (Step S142).

As described above, when carrying out the image sensing while displaying an image, this embodiment can achieve power savings without increasing the shutter time lag, by using the low operating frequency before the recording operation is started or except during the recording operation.

When the sensed image is not displayed and thus less power saving effect is available, this embodiment can give priority to the processing speed and avoid increasing the shutter time lag more reliably.

Needless to say, the object of the present invention can also be achieved by a storage medium containing the software program code that implements the functions of the



above embodiments: it is supplied to an image sensing apparatus (image sensing apparatus 100), whose computer (or a CPU or MPU) (system control circuit 50) then reads the program code out of the storage medium and executes it.

5        In that case, the program code itself read out from the storage medium will implement the new functions of the above embodiments, and the storage medium which stores the program code will constitute the present invention.

10        As the storage medium for supplying the program code, for example, a floppy disk, hard disk, optical disk, magneto-optical disk, CD-ROM, CD-R, magnetic tape, non-volatile memory card, ROM, or the like may be used.

15        The functions of the above embodiments may be implemented not only by the program code read out and executed by the computer, but also by part or all of the actual processing executed, in accordance with instructions from the program code, by an OS (operating system) running on the computer.

20        Furthermore, the functions of the above embodiments may also be implemented by part or all of the actual processing executed by a CPU or the like contained in a function expansion card inserted in the computer or a function expansion unit connected to the computer if the processing is performed in accordance with instructions  
25        from the program code that has been read out of the storage medium and written into memory on the function expansion card or unit.

As many apparently widely different embodiments of the present invention can be made without departing from the spirit and scope thereof, it is to be understood that the invention is not limited to the specific embodiments  
5 thereof except as defined in the claims.

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2226  
2227  
2228  
2229  
2230  
2231